





LED-BLITZLEUCHE SOLISTA | LED-BEACON SOLISTA

- Sehr geringe Stromaufnahme
- Ultra low current consumption
- Hohe Zuverlässigkeit
- High reliability
- Einzelgerät oder als Blitz- und Soundkombination
- Stand alone or combined sounder & beacon version
- Passend für Universalsockel S-, D- und U-Base
- Shallow-, Deep- and U-Base compatible
- Kompakte Bauform
- Compact size


CLARIFIRE LED AV UNIT




CONVENTIONAL LED BEACON



ROLP LED AV UNIT



SQUASHNI MICRO LED AV UNIT



SPEZIFIKATIONEN / SPECIFICATIONS

MODEL	Solista Beacon (stand - alone beacon)**	ROLP Solista (Beacon integrated with Roshni LP)**	Clarifire Solista (Beacon integrated with Clarifire)**	Solista SQM*** (Beacon fits onto Squashni Micro)
OPERATING VOLTAGE	9 - 28VDC*			9 - 28VDC
CURRENT CONSUMPTION	3mA / 6mA at 24VDC User selectable	20mA with sounder	23mA with typical on tone message	3mA / 6mA at 24VDC User selectable (Does not include sounder current)
FLASH RATE	0.5Hz/1Hz User selectable	1Hz fixed		0.5Hz / 1Hz User selectable
FLASH INTENSITY	> 0.5Cd at 3mA > 1.0Cd at 6mA	> 0.5Cd		> 0.5Cd at 3mA > 1.0Cd at 6mA
OPERATING TEMPERATURE	-10°C to + 55°C			
LINE MONITORING	Reverse polarity			
IP RATING	Shallow Base = IP54, Deep Base = IP65, U-Base = IP65			IP42
BASE OPTIONS	Fulleon bayonet bases, Shallow, Deep, "U"			Specific fit to Squashni Micro
LENS COLOUR	Red			
BODY COLOUR	Red or White			
WEIGHT	0.1kg	0.3kg	0.3kg	0.1kg / 0.26kg with sounder
CONSTRUCTION	ABS Body / polycarbonate lens			
APPROVALS	N/A	VdS	N/A	N/A

* 110 bis 230VAC mit Powered Base / 110 to 230VAC with Powered Base
 ** ACHTUNG! Die Sockel S-, D- oder U- Base müssen separat bestellt werden! / ATTENTION! Bases S-, D- or U have to be ordered separately!
 *** ACHTUNG! Die Sirene Squashni Micro (SQM) muss separat bestellt werden! / ATTENTION! Sounder Squashni Micro has to be ordered separately!